

92/93 Series – Wired Remote Kits

Part Numbers

9602	2 Function Wired Remote Kit
9604	4 Function Wired Remote Kit
9606	6 Function Wired Remote Kit
9610	10 Function Wired Remote Kit
9616	16 Function Wired Remote Kit
9620	20 Function Wired Remote Kit

Kit Includes

- 1 x Wired Remote with curly cable
- 1 x Interface PCB (fits in Receiver)
- 1 x RS232 Link Cable
- 1 x Instructions



9610



9602



9604



9606



9610



9616



9620

IP WIRED REMOTE

A Lodar Wired Remote is a Transmitter without the "Radio Module" wired directly to the Receiver; it will guarantee control when RF conditions are poor, that is for example when in the vicinity of a high powered transmitter that drowns out Lodar: most unusual. The advantage of a Lodar Wired Remote is that all the pre-programmed features are retained; for example interlocks, parallel or continuous master, master on delay and other special features.

A Lodar wired Remote is a very cost effective way to provide a backup to the radio system with no extra wiring required.

SPECIFICATION

SWITCH - Type	Tactile Dome on PCB Keypad
BATTERY	Not required powered from Receiver via RS232 connection
INDICATOR	
Type	1 x Red LED
Off	Remote OFF (The STOP Button has been pressed and released)
Slow Flash	Remote is ON and ready to use (The SET button has been pressed and released)
On	Remote IN USE (A STOP, SET or Function Button is being pressed)
CURLY CABLE	
Length at rest	1 Metre (3 Ft)
Max Extension	3 Metres (10 Ft)
Material	Poly Urethane
PROTECTION	
Reverse polarity	Protected
IP Rating	67
Conformal coating	No